

CLASSIC

STEP DOWN TRANSFORMERS

MODELS GP95T-16gsa / GP16P40gsa



GP16P40gsa

GP95T-16gsa Shown attached to standard junction box.

FUNCTION

The step-down transformers provided by Lencore are industry listed by UL and/or CSA for electrical safety. The transformers step down from 120 AC voltage to 16v AC voltage. Model GP95T-16gsa can handle up to 78 masking units. Where paging is incorporated, each transformer handles approximately 33 speakers. Model GP16P40gsa plug-in transformer is typically used when a project utilizes 6 speakers or less.

SPECIFICATIONS

GP95T-16gsa
16V/95VA

GP16P40gsa
16V/40VA

SIZE

GP95T-16gsa
4 1/4" x 4 1/4" x 4"

GP16P40gsa
2 1/2" x 3 3/8" x 2"

POWER RATING

GP95T-16gsa
95VA

GP16P40gsa
40VA

POWER REQUIREMENT

GP95T-16gsa
120v AC, 60 HZ

GP16P40gsa
120v AC, 60 HZ

FUSE

GP95T-16gsa
6-Amp Reset Circuit Breaker

GP16P40gsa
N/A